

Social Alarm S35 Pendant Transmitter

www.boschsecurity.com



BOSCH

Invented for life



- ▶ Easy to use and compact
- ▶ Alarm triggering in 2 ways : button or cord
- ▶ IP64 waterproof
- ▶ Battery life-time of 3 years
- ▶ Automatic radio daily message

Its compact size, waterproof case and ease of operation make the S35 Pendant Transmitter the perfect solution for use at home with a Carephone. The alarm is triggered by pulling the cord or pressing the red button, releasing a call to the Carephone. The S35 Pendant Transmitter can be worn clipped on clothing or around the neck with the pull-cord.

Functions

The S35 Pendant Transmitter is a radio transmitter designed to ensure a secure and easy transmission of an alarm anywhere and at any time. This can be done either by pressing the button or pulling the cord of the S35 Pendant Transmitter. A call for help is then activated and the LED indicator of the transmitter will blink once. In the meantime, the button and the LED indicator of the Carephone receiver will start blinking. An alarm/event data is displayed on the unit and is stored in the buffer of the device. Cancelling an alarm can be done on the Carephone or remotely by the Social alarm center.

The S35 Pendant Transmitter offers an IP64 waterproof protection and has a built-in automatic battery monitoring with battery low transmission. To ensure correct functioning, it will send an automatic radio daily message to the receiver through radio monitoring.

Certifications and Approvals

CE

R&TTE 1999/5/EC

LVD 73/23/EEC

EMC 89/336/EEC

EN 50130-4

EN 300220-1

EN 60950-1

EN 55022

Parts Included

Quant.	Component
1	S35 Pendant Transmitter

Technical Specifications

Dimensions (H x W x D)	75 x 40 x 25 mm
Weight	40 g
Frequency	869.2125 MHz
Protection class	IP 64
Power supply	3V lithium battery CR2032
Consumption	Transmission: < 25 mA Idle mode: < 2 µA
Battery life	3 years, under the following conditions: 3 alarms transmissions without repetition per day and 1 daily test transmission (incl. battery status)
Battery alarm	at approx. 20 % remaining
Automatic battery test	daily check and at every alarm
Permissible temperature	0 °C to 55 °C
Stability (0 to +55 °C)	< ± 2.5 KHz
Modulation	FSK
Antenna	Integrated
Radiated power	2 mW
Transmission time	3 x 700 ms
Pause between transmissions	800 ms
Minimum range in free field	250 m

Ordering Information

S35 Pendant Transmitter

Order number **CRS-CP-S35**

Accessories

Wall bracket for S35 Pendant Transmitter

Set of 10 pieces

Order number **CRS-SB-X2700**

Wall mount fixing for S35 Pendant Transmitter

Set of 5 pieces

Order number **CRS-832-44**

Detachable cord

For S35 Pendant Transmitter or S37 Wristband Transmitter.

Set of 10 pieces.

Order number **CRS-C-080**

CR2032 3V Battery for S35 Pendant Transmitter

Set of 5 pieces

Order number **CRS-P-302**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6258 5511
Fax: +65 6571 2698
apr.securitysystems@bosch.com
www.boschsecurity.asia